

2000 W INVERTER GENERATOR

SG2500i



PRODUCT DATA	
Dimensions L x W x H	520 x 270 x 440 mm
Engine	Single cylinder, 4-stroke petrol motor
Power	3 hp
Fuel type	Petrol
Voltage regulation	Inverter
Rated voltage	230 V~
Rated/Max. / Peak Power	1600 / 2000 W
Sockets	2x 230V, 1x USB-A, 1x USB-C
Starter type	Pull starter
Parallel circuit	No
Overload protection	Yes
Oil monitor	Yes
Sound pressure level (LwA)	71.74 dB
CO² output	874 g/kWh

LOGISTICAL DATA	
Weight net / gross	18.5 / 20 kg
Packaging dimensions	511 x 330 x 487 mm
Item number	5906240903
EAN	4046664300786
20 containers	288 pcs.
40 containers	592 pcs.
40 HQ containers	740 pcs.



User-friendly operation



Large 6.3 litre fuel tank



Transport handle



1600 W nominal power, 2000 W maximum power for devices with sensitive electronics, power tools, etc.



Rubber feet to protect against vibration



Easy start using pull starter

2x USB ports



2 x 230 V sockets



Oil warning indicator



Energy saving switch



Overload protection



Fuel-saving



Lightweight



Transportable

